

Датчики ветра PRO-Modbus

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: ahm@nt-rt.ru || сайт: <https://lambrecht.nt-rt.ru/>



PRO-Modbus Wind Direction Sensor

APPLICATIONS

- Professional meteorological applications
- Building automation
- Photovoltaic systems
- Industrial meteorology

RUGGED FOR YEAR-ROUND USE

The Modbus RTU Interface simplifies the integration of the sensors into networks and allows the construction of long communication distances. PRO-Modbus sensors are predestined for use in areas subject to lightning. Their improved protection against electrostatic discharge in combination with the interference-proof communication ensures a high integrity of your data. PRO-Modbus sensors with their integrated, regulated heating system provide you with reliable work as a tireless endurance runner in all-year use and in most climatic zones.

- Improved protection against electrostatic discharge
- Especially robust due to reinforced axis
- Low starting values of < 0.5 m/s
- Very high resolution of measuring values

Data sheet

Professional Line	PRO-Modbus
Id-No.:	00.14523.131030
Measuring range:	0...360°
Accuracy:	2°
Resolution:	<1°
Starting value:	< 0.5 m/s
Output:	Modbus RTU
Range of application:	Temperature: -40...+70 °C heated; wind speed: max. gusts 100 m/s; rel. humidity: 0...100 % r.h.
Supply voltage:	24 VDC (6...32 VDC)
Current consumption:	Max. 800 mA at 24 VDC and max. heating; 13 mA at 24 VDC and inactive heating (The heating can be deactivated via software tool. This allows the current consumption to be reduced to 8.5 mA at 24 VDC.)
Measuring elements:	Wind vane; aluminum; specially coated
Measuring principle:	Hall Sensor Array, non-contact
Heating data:	18 W heating; electronically controlled (The heating within the sensor head prevents blocking of the moving parts under most climatological conditions.)
Housing:	Seawater-resistant aluminum; IP 65 in upright position; M12 cable-plug connection; stainless steel nut and lock washer
Weight:	0.4 kg
Accessories (order separately):	32.14567.060010 Sensor cable, 15 m, 4 pole, M12 plug 32.14567.060000 Sensor cable, 12 m, 4 pole, M12 plug



PRO-Modbus Wind Speed Sensor

APPLICATIONS

- Professional meteorological applications
- Building automation
- Photovoltaic systems
- Industrial meteorology

EXTREMELY ROBUST AND WITH MODBUS RTU

The Modbus RTU Interface simplifies the integration of the sensors into networks and allows the construction of long communication distances. PRO-Modbus sensors are predestined for use in areas subject to lightning. Their improved protection against electrostatic discharge in combination with the interference-proof communication ensures a high integrity of your data. PRO-Modbus sensors with their integrated, regulated heating system provide you with reliable work as a tireless endurance runner in all-year use and in most climatic zones.

- Improved protection against electrostatic discharge
- Especially robust due to reinforced axis
- High measuring range of 75 m/s
- Low starting values of < 0.5 m/s
- Very high resolution of measuring values

Data sheet

Professional Line	PRO-Modbus
Id-No.:	00.14524.101030
Measuring range:	0.5...75 m/s
Accuracy:	0.3 m/s < 10 m/s; 0.5 m/s...60 m/s
Resolution:	< 0.1 m/s
Starting value:	< 0.5 m/s
Output:	Modbus RTU
Range of application:	Temperature: -40...+70 °C heated; wind speed: max. gusts 100 m/s; rel. humidity: 0...100 % r.h.
Supply voltage:	24 VDC (6...32 VDC)
Current consumption:	Max. 800 mA at 24 VDC and max. heating; 13 mA at 24 VDC and inactive heating (The heating can be deactivated via software tool. This allows the current consumption to be reduced to 8.5 mA at 24 VDC.)
Measuring elements:	Aluminum; specially coated; 3 armed cup rotor
Measuring principle:	Hall Sensor Array, non-contact
Heating data:	18 W heating; electronically controlled (The heating within the sensor head prevents blocking of the moving parts under most climatological conditions.)
Housing:	Seawater-resistant aluminum; IP 65 in upright position; M12 cable-plug connection; stainless steel nut and lock washer
Weight:	0.35 kg
Accessories (order separately):	32.14567.060010 Sensor cable, 15 m, 4 pole, M12 plug 32.14567.060000 Sensor cable, 12 m, 4 pole, M12 plug

По вопросам продаж и поддержки обращайтесь:

Алматы (727)345-47-04
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +(727)345-47-04

Беларусь +(375)257-127-884

Узбекистан +998(71)205-18-59

Киргизия +996(312)96-26-47

эл.почта: ahm@nt-rt.ru || сайт: <https://lambrecht.nt-rt.ru/>